

FLUX

FLUXMETER



DESCRIPTION

The FLUXMETER 20KA (associated with SEREM Ammeter Clamp) makes it possible to measure current up to 20KA. The SEREM fluxmeter is an accurate instrument for daily use under the rugged conditions imposed by industry including corrosive chemical atmospheres and high temperatures. It is completely insensitive to high magnetic fields.

-POWER SUPPLY: Built-in 9V battery (6LF22 type), autonomy : 1000 hours



FEATURES

CONFIGURATION

- Version for PAR-ROT SEREM clamp.
- Version for rotative SEREM clamp.
- Version for round or square SEREM clamp.

INPUT 1 - current

- Range from 0 to 19.99KA_{dc}

POWER SUPPLY

- Battery 9V (6LR61 type)

ACCURACY

- > 0,5% +-1pt

MAGNETIC FIELDS

- up to 150 Gauss in X, Y, Z dimensions

CASING

- ABS isolated box, junction by connector LEMO 0B-5pts
- On / Off press button

DISPLAY

- LCD display 2000 points height : 12,5mm
- Low batt. indicator and overheating probe indicator

PRICE On quote only

WEB LINK [Click here](#)

SECTOR

USAGE

WEIGHT 220 gramme

LENGTH 115 mm

WIDTH 70 mm

HEIGHT 45 mm

CUSTOMS CODE 90 30 33 70

C. OF ORIGIN France

GUARANTEE 1 year

CERTIFICATION CE

CONTACT commercial@serem-electronics.com