

## FLUX

## FLUXMETER



### DESCRIPTION

The FLUXMETER 20KA (associated with SEREM Ammeter Clamp) makes it possible to measure current up to 20KA. The SEREM fluxmeter is an accurate instrument for daily use under the rugged conditions imposed by industry including corrosive chemical atmospheres and high temperatures. It is completely insensitive to high magnetic fields.



### FEATURES

#### CONFIGURATION

- Version for PAR-ROT SEREM clamp.
- Version for rotative SEREM clamp.
- Version for round or square SEREM clamp.

#### INPUT 1 - current

- Range from 0 to 19.99KA<sub>dc</sub>

#### POWER SUPPLY

- Battery 9V (6LR61 type)

#### ACCURACY

- > 0,5% +-1pt

#### MAGNETIC FIELDS

- up to 150 Gauss in X, Y, Z dimensions

#### CASING

- ABS isolated box, junction by connector LEMO 0B-5pts
- On / Off press button

#### DISPLAY

- LCD display 2000 points height : 12,5mm
- Low batt. indicator and overheating probe indicator

**PRICE** On quote only

**WEB LINK** [Click here](#)

**SECTOR**

**USAGE**

**WEIGHT** 220 g

**LENGTH** 115 mm

**WIDTH** 70 mm

**HEIGHT** 45 mm

**CUSTOMS CODE** 90 30 39 00 91

**C. OF ORIGIN** France

**GUARANTEE** 1 year

**CERTIFICATION** CE

**CONTACT** [commercial@serem-electronics.com](mailto:commercial@serem-electronics.com)